

Net-960CE-X (WinCE) models Comparison table



Net-960CE-X
MDT platform

Key Features	Net-960CE-X1	Net-960CE-X2	Net-960CE-X3
S/W Development	SDK Available Visual C++ .0	Same as -X1	Same as -X1
O/S	Windows CE 4.2 Core License *	Same as -X1	Same as -X1
CPU	32 bit 100MHZ	Same as -X1	Same as -X1
Memory RAM Flash	16 MB 8 MB	16 MB 16 MB	32 MB 16 MB
Display	Graphic Monochrome 240x64 Pixels	Same as -X1	Same as -X1
ScreenLess option (Under Dashboard model)	Optional	Same as -X1	Same as -X1
GPS/GPRS (Built-in)	—	—	Yes
Comm & Connectivity Ports	-RS232 x 2 -USB Device	-RS232 x 4 -1 SAE 1708 (optional) -USB Device	Same as -X2
Real Time Clock	—	—	Yes
Audio Codec	—	—	Yes
Control I/O Signals	2 Automotive input signals with counter functionality and 1 O/C output	Same as -X1	3 Automotive input signals with counter functionality and 2 O/C outputs
Dallas ID Reader Support	Yes	Same as -X1	Same as -X1
Power On/Off Software Control	Yes	Same as -X1	Same as -X1
Power	8V-30V car battery.	Same as -X1	Same as -X1
Peripherals Support	Printers or Swipe Card or Bar-Code Laser Scanner Via RS-232 port, Keyboard Via optional RS/232 PS/2 external Adapter.	Same as -X1	Same as -X1
Protective Back Cover	Optional	Same as -X1	Same as -X1

Full product information, including product specifications and SW & HW manuals, can be found at:
Net-960CE-X <http://www.micronet.co.il/Net-960CE-X.html>

Our Developers Packages come with a 30 days Money-Back-Guarantee!
For details check at: http://www.micronet.co.il/Development_Tool_Kit.html